



Firmware Release Note

Prestige 202H
Standard version

Release 3.40(NV.0)C0

Date:	June 17 2003
Author:	June Lee

ZyXEL Prestige 202H Standard Version release 3.40(NV.0)C0 Release Note

Date: June 17, 2003

Supported Platforms:

ZyXEL P202H

Versions:

ZyNOS F/W Version : V3.40(NV.0) | 6/17/2003 9:06:15
BootBase : V2.09 | 9/6/2002 16:06:05

Notes:

The P202H, is 3rd generation of ZyXEL ISDN product family. It is a ISDN router for small/medium office to have Internet access and LAN-to-LAN application through ISDN connection over the ISDN line.

Known Issues:

Features:

Modifications in V 3.40(NV.0) | 06/17/2003

1. Change to FCS version.

Modifications in V 3.40(NV.0)b2 | 05/27/2003

1. [FEATURE ENHANCED]
Integrate Web GUI.
2. [FEATURE ENHANCED]
Merge Phase III VPN feature.

Modifications in V 3.40(NV.0)b1 | 04/18/2003

1. [FEATURE CHANGED]
Porting P202H for OBM from P202H for DT (with source code 3.40(IJ.0)b5)

Annex A CI Command List

Command Class List Table		
System Related Command	Exit Command	Ethernet Related Command
IP Related Command	IPSec Related Command	

System Related Command

[Home](#)

Command				Description
sys				
	callhist			
		display		display call history
		remove	<index>	remove entry from call history
	countrycode		[countrycode]	set country code
	date		[year month date]	set/display date
	domainname			display domain name
	edit		<filename>	edit a text file
	extraphnum			maintain extra phone numbers for outcalls
		add	<set 1-3> <1st phone num> [2nd phone num]	add extra phone numbers
		display		display extra phone numbers
		node	<num>	set all extend phone number to remote node <num>
		remove	<set 1-3>	remove extra phone numbers
		reset		reset flag and mask
	feature			display feature bit
	firewall			
		acl		
			disp	display specific ACL set # rule #, or all ACLs.
		active	<yes/no>	active firewall or deactivate firewall
		clear		clear firewall log
		cnt		
			disp	display firewall log type and count.
			clear	clear firewall log count.
		disp		display firewall log
		online		set firewall log online.
		pktdump		dump the 64 bytes of dropped packet by firewall
		update		update firewall
		tcprst		
			rst	set TCP reset sending on/off.
			rst113	set TCP reset sending for port 113 on/off.
			display	display TCP reset sending setting.
		dos		
			smtp	set SMTP DoS defender on/off
			display	display SMTP DoS defender setting.
			ignore	set if firewall ignore DoS in lan/wan/dmz/wlan
		ignore		
			triangle	set if firewall ignore triangle route in lan/wan/dmz/wlan
	hostname		[hostname]	display system hostname
	log			
		clear		clear log error
		disp		display log error
		online	[on/off]	turn on/off error log online display

	stdio		[second]	change terminal timeout value
	trcdisp			monitor packets
	syslog			
		server	[destIP]	set syslog server IP address
		facility	<FacilityNo>	set syslog facility
		type	[type]	set/display syslog type flag
		mode	[on off]	set syslog mode
	version			display RAS code and driver version
	view		<filename>	view a text file
	wdog			
		switch	[on off]	set on/off wdog
		cnt	[value]	display watchdog counts value: 0-34463
	atsh			display MRD field
	socket			display system socket information
	filter			
		netbios		
			disp	display netbios filter status
			config <0:LAN to WAN, 1:WAN to LAN, 2:LAN to DMZ, 3:IPSec passthrough, 4:Trigger Dial> <on off>	config netbios filter
	ddns			
		debug	<level>	enable/disable ddns service
		display	<iface name>	display ddns information
		restart	<iface name>	restart ddns
		logout	<iface name>	logout ddns
	cpu			
		display		display CPU utilization

Exit Command

[Home](#)

Command				Description
exit				exit smt menu

Ethernet Related Command

[Home](#)

Command				Description
ether				
	config			display LAN configuration information
	driver			
		cnt		
			disp <name>	display ether driver counters
		status	<ch name>	see LAN status
	version			see ethernet device type

IP Related Command

[Home](#)

Command				Description
ip				
	address		[addr]	display host ip address
	alias		<iface>	alias iface
	aliasdis		<0 1>	disable alias
	arp			
		status	<iface>	display ip arp status
	dhcp		<iface>	
		client		
			release	release DHCP client IP
			renew	renew DHCP client IP

	mode	<server relay none client>	set dhcp mode
	relay	server <serverIP>	set dhcp relay server ip-addr
	reset		reset dhcp table
	server		
		probecount <num>	set dhcp probe count
		dnsserver <IP1> [IP2] [IP3]	set dns server ip-addr
		winsserver <winsIP1> [<winsIP2>]	set wins server ip-addr
		gateway <gatewayIP>	set gateway
		hostname <hostname>	set hostname
		initialize	fills in DHCP parameters and initializes (for PWC purposes)
		leasetime <period>	set dhcp leasetime
		netmask <netmask>	set dhcp netmask
		pool <startIP> <numIP>	set dhcp ip pool
		renewaltime <period>	set dhcp renew time
		rebindtime <period>	set dhcp rebind time
		reset	reset dhcp table
		server <serverIP>	set dhcp server ip for relay
		dnsorder [router isp]	set dhcp dns order
	status	[option]	show dhcp status
	static		
		delete <num> all	delete static dhcp mac table
		display	display static dhcp mac table
		update <num> <mac> <ip>	update static dhcp mac table
dns			
	stats		
		clear	clear dns statistics
		disp	display dns statistics
icmp			
	status		display icmp statistic counter
	discovery	<iface> [on off]	set icmp router discovery flag
ifconfig		[iface] [ipaddr] [broadcast <addr> mtu <value> dynamic]	configure network interface
ping		<hostid>	ping remote host
route			
	status	[if]	display routing table
	add	<dest_addr default>[/<bits>] <gateway> [<metric>]	add route
	addiface	<dest_addr default>[/<bits>] <gateway> [<metric>]	add an entry to the routing table to iface
	addprivate	<dest_addr default>[/<bits>] <gateway> [<metric>]	add private route
status			display ip statistic counters
udp			
	status		display udp status
tcp			
	status	[tcb] [<interval>]	display TCP statistic counters
xparent			
	join	<iface1> [<iface2>]	join iface2 to iface1 group
	break	<iface>	break iface to leave ipxparent group

Command	Description
---------	-------------

ipsec				
	debug	<1 0>		turn on/off trace for IPsec debug information
	ipsec log disp			show IPsec log, same as menu 27.3
	route	lan	<on/off>	After a packet is IPsec processed and will be sent to LAN side, this switch is to control if this packet can be applied IPsec again.
				Remark: Command available since 3.50(WA.3)
		wan	<on/off>	After a packet is IPsec processed and will be sent to WAN side, this switch is to control if this packet can be applied IPsec again.
				Remark: Command available since 3.50(WA.3)
	show_runtime	sa		display runtime phase 1 and phase 2 SA information
		spd		When a dynamic rule accepts a request and a tunnel is established, a runtime SPD is created according to peer local IP address. This command is to show these runtime SPD.
	switch	<on/off>		As long as there exists one active IPsec rule, all packets will run into IPsec process to check SPD. This switch is to control if a packet should do this. If it is turned on, even there exists active IPsec rules, packets will not run IPsec process.
	timer	chk_my_ip	<1~3600>	- Adjust timer to check if WAN IP in menu is changed
				- Interval is in seconds
				- Default is 10 seconds
				- 0 is not a valid value
		chk_conn.	<0~255>	- Adjust auto-timer to check if any IPsec connection has no traffic for certain period. If yes, system will disconnect it.
				- Interval is in minutes
				- Default is 2 minutes
				- 0 means never timeout
		update_peer	<0~255>	- Adjust auto-timer to update IPsec rules which use domain name as the secure gateway IP.
				- Interval is in minutes
				- Default is 30 minutes
				- 0 means never update
				Remark: Command available since 3.50(WA.3)
	updatePeerIp			Force system to update IPsec rules which use domain name as the secure gateway IP right away.
				Remark: Command available since 3.50(WA.3)
	dial	<rule #>		Initiate IPsec rule <#> from ZyWALL box
				Remark: Command available since 3.50(WA.3)
	display	<rule #>		Display IPsec rule #